Silicon P-Channel MOS FET

HITACHI

ADE-208-143

Application

Low frequency power amplifier

Complementary pair with 2SK2220, 2SK2221

Features


- High power gain
- Excellent frequency response
- High speed switching
- Wide area of safe operation
- Enhancement-mode
- Good complementary characteristics
- Equipped with gate protection diodes

Ordering Information

| Type No. | V_{DSX} | |
|----------|-----------|---|
| 2SJ351 | –180 V | _ |
| 2SJ352 | –200 V | |



Outline



Absolute Maximum Ratings ($Ta = 25^{\circ}C$)


| Item | | Symbol | Ratings | Unit |
|---|--------|------------------------------|-------------|------|
| Drain to source voltage | 2SJ351 | $V_{\scriptscriptstyle DSX}$ | -180 | V |
| | 2SJ352 | | -200 | |
| Gate to source voltage | | V_{GSS} | ±20 | V |
| Drain current | | I _D | -8 | А |
| Body to drain diode reverse drain current | | I _{DR} | -8 | А |
| Channel dissipation | | Pch*1 | 100 | W |
| Channel temperature | | Tch | 150 | °C |
| Storage temperature | | Tstg | -55 to +150 | °C |


Note: 1. Value at $T_c = 25^{\circ}C$


Electrical Characteristics ($Ta = 25^{\circ}C$)

| Item | | Symbol | Min | Тур | Max | Unit | Test conditions |
|------------------------------|-----------|----------------------|-------|------|-------|------|---|
| Drain to source | 2SJ351 | $V_{(BR)DSX}$ | -180 | _ | _ | ٧ | $I_D = -10 \text{ mA}, V_{GS} = 10 \text{ V}$ |
| breakdown voltage | 2SJ352 | | -200 | _ | _ | | |
| Gate to source break voltage | kdown | $V_{(BR)GSS}$ | ±20 | _ | _ | V | $I_{G} = \pm 100 \ \mu A, \ V_{DS} = 0$ |
| Gate to source cutof | f voltage | $V_{GS(off)}$ | -0.15 | _ | -1.45 | V | $I_D = -100 \text{ mA}, V_{DS} = -10 \text{ V}$ |
| Drain to source satu voltage | ration | $V_{\text{DS(sat)}}$ | _ | _ | -12 | V | $I_D = -8 \text{ A}, V_{GD} = 0^{*1}$ |
| Forward transfer adr | mittance | $ y_{fs} $ | 0.7 | 1.0 | 1.4 | S | $I_D = -3 \text{ A}, V_{DS} = -10 \text{ V}^{*1}$ |
| Input capacitance | | Ciss | _ | 800 | _ | pF | $V_{GS} = 5 \text{ V}, V_{DS} = -10 \text{ V},$ |
| Output capacitance | | Coss | _ | 1000 | _ | pF | f = 1 MHz |
| Reverse transfer cap | oacitance | Crss | _ | 18 | _ | pF | _ |
| Turn-on time | | t _{on} | _ | 320 | _ | ns | $V_{DD} = -30 \text{ V}, I_{D} = -4 \text{ A}$ |
| Turn-off time | | t _{off} | _ | 120 | _ | ns | |


Note: 1. Pulse test








Unit: mm





| | | 0.0 | _ | | | _ | | |
|----------|-----|-----|----|----------|----|------------|------|-----|
| | | | ١, | - | +1 | .0 | | |
| | ш | | | 1 | | ₽ \ | | |
| 5.45 ± 0 | 0.5 | | | | | 5.4 | 45 ± | 0.5 |

| Hitachi Code | TO-3P |
|--------------------------|----------|
| JEDEC | |
| EIAJ | Conforms |
| Weight (reference value) | 5.0 g |

Cautions

- 1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
- 2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
- 3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
- 4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
- 5. This product is not designed to be radiation resistant.
- 6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
- 7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

HITACHI

Hitachi, Ltd.

Semiconductor & Integrated Circuits.

Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan Tel: Tokyo (03) 3270-2111 Fax: (03) 3270-5109

Tel: Tokyo (03) 3270-2111 Fax: (03) 3270-5109

URL NorthAmerica : http:semiconductor.hitachi.com/

URL NorthAmerica Europe Asia (Singapore) Asia (Taiwan) Asia (HongKong)

: http://www.hitachi-eu.com/hel/ecg
pore) : http://www.has.hitachi.com.sg/grp3/sicd/index.htm
n) : http://www.hitachi.com.tw/E/Product/SICD_Frame.htm
long) : http://www.hitachi.com.hk/eng/bo/grp3/index.htm

Japan : http://www.hitachi.co.jp/Sicd/indx.htm

For further information write to:

Hitachi Semiconductor (America) Inc. 179 East Tasman Drive, San Jose,CA 95134 Tel: <1> (408) 433-1990 Fax: <1>(408) 433-0223 Hitachi Europe GmbH Electronic components Group Dornacher Stra§e 3 D-85622 Feldkirchen, Munich Germany Tel: <49> (89) 9 9180-0

Fax: <49> (89) 9 29 30 00

Hitachi Europe Ltd.

Electronic Components Group.

Whitebrook Park Lower Cookham Road Maidenhead

Berkshire SL6 8YA, United Kingdom Tel: <44> (1628) 585000

Tel: <44> (1628) 585000 Fax: <44> (1628) 778322 Hitachi Asia Pte. Ltd. 16 Collyer Quay #20-00 Hitachi Tower Singapore 049318 Tel: 535-2100 Fax: 535-1533

Hitachi Asia Ltd.
Taipei Branch Office
3F, Hung Kuo Building. No.167,
Tun-Hwa North Road, Taipei (105)
Tel: <886> (2) 2718-3666

Fax: <886> (2) 2718-8180

Hitachi Asia (Hong Kong) Ltd.
Group III (Electronic Components)
7/F., North Tower, World Finance Centre,
Harbour City, Canton Road, Tsim Sha Tsui,
Kowloon, Hong Kong
Tel: <852> (2) 735 9218

Fax: <852> (2) 735 9218 Fax: <852> (2) 730 0281 Telex: 40815 HITEC HX

Copyright ' Hitachi, Ltd., 1999. All rights reserved. Printed in Japan.