IM6402/D, IM6403/D, IM6402/W, IM6403/W Universal Asynchronous Receiver Transmitter (UART)



GENERAL DESCRIPTION

The IM6402 and IM6403 are CMOS/LSI UARTs for interfacing computers or microprocessors to asynchronous serial data channels. The receiver converts serial start, data, parity and stop bits to parallel data verifying proper code transmission, parity, and stop bits. The transmitter converts parallel data into serial form and automatically adds start, parity, and stop bits.

The data word length can be 5, 6, 7 or 8 bits. Parity may be odd or even, and parity checking and generation can be inhibited. The stop bits may be one or two (or one and one-half when transmitting 5 bit code).

The IM6402 and IM6403 can be used in a wide range of applications including modems, printers, peripherals and remote data acquisition systems. CMOS/LSI technology permits clock frequencies up to 4.0 MHz (250K Baud), an improvement of 10 to 1 over previous PMOS UART designs. Power requirements, by comparison, are reduced from 670 mW to 10 mW. Status logic increases flexibility and simplifies the user interface.

The IM6402 differs from the IM6403 in the use of five device pins as indicated in Table 1 and Figure 1.

FEATURES


- ◆ Low Power—Less Than 10 mW Typ. at 2 MHz
- Programmable Word Length, Stop Bits and Parity
- Automatic Data Formatting and Status Generation
- Compatible With Industry Standard UART's (IM6402)
- On-Chip Oscillator With External Crystal (IM6403)
- Operating Voltage—IM6402/03: 5V

Table 1

Pin	IM6402	IM6403 w/XTAL	IM6403 w/EXT CLOCK			
2	N/C	Divide Control	Divide Control			
17	RRC	XTAL	External Clock Input			
19	Tri-State	Always Active	Always Active			
22	Tri-State	Always Active	Always Active			
40	TRC	XTAL	V _{SS}			

ORDERING INFORMATION

Part Number	Temperature	Form	
IM6402/D	+ 25°C	Dice	
IM6403/D	+ 25°C	Dice	
IM6402/W	+ 25°C	Wafer	
IM6403/W	+ 25°C	Wafer	



INTERSIL'S SOLE AND EXCLUSIVE WARRANTY OBLIGATION WITH RESPECT TO THIS PRODUCT SHALL BE THAT STATED IN THE WARRANTY ARTICLE OF THE CONDITION OF SALE.

THE WARRANTY SHALL BE EXCLUSIVE AND SHALL BE IN LIEU OF ALL OTHER WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING THE IMPLIED WARRANTIES OF MERICHANTABILITY AND FITNESS FOR A PARTICULAR USE.


IM6402/D, IM6403/D, IM6402/W, IM6403/W



ABSOLUTE MAXIMUM RATINGS

NOTE: Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions above those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may cause device failures.

CHIP TOPOGRAPHY



INTERSIL'S SOLE AND EXCLUSIVE WARRANTY OBLIGATION WITH RESPECT TO THIS PRODUCT SHALL BE THAT STATED IN THE WARRANTY ARTICLE OF THE CONDITION OF SALE. THE WARRANTY SHALL BE EXCLUSIVE AND SHALL BE IN LIEU OF ALL OTHER WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR USE.

www.blm6402/D, IM6403/D, IM6402/W, IM6403/W

DC CHARACTERISTICS $V_{DD} = 5.0V \pm 10\%$, $T_A = 25^{\circ}C$

	Symbol	Parameter	Conditions	Min	Тур	Max	Units
1	V _{IH}	Input Voltage High		V _{DD} - 2.0			V
2	VIL	Input Voltage Low				0.8	٧
3	l _{IL}	Input Leakage (Note 1)	$V_{SS} \le V_{IN} \le V_{DD}$	-5.0		5.0	μΑ
4	V _{OH}	Output Voltage High	$I_{OH} = -0.2 \text{ mA}$	2.4			٧
5	V _{OL}	Output Voltage Low	I _{OL} = V _{DD}			0.45	>
6	loL	Output Leakage	V _{SS} ≤ V _{OUT} ≤ V _{CC}	-5.0		5.0	μΑ
7	Icc	Power Supply Current Standby	V _{IN} = GND or V _{CC}		1.0		μΑ

NOTE 1: Except IM6403 XTAL input pins.

AC CHARACTERISTICS $V_{CC} = 5.0V \pm 10\%$, $C_L = 50 \text{ pF}$, $T_A = 25^{\circ}\text{C}$

	Symbol	Parameter	Conditions	Min	Тур	Max	Units
1	fc	Clock Frequency IM6402		DC	3.0	1.0	MHz
2	fCRYSTAL	Crystal Frequency IM6403	1		4.0		MHz
3	tpw	Pulse Widths CRL, DRR, TBRL	See Timing Diagrams	400	50		ns
4	t _{MR}	Pulse Width MR	(Figures 4, 5, 6)	510	200		ns
5	t _{DS}	Input Data Setup Time	1	300	20		ns
6	t _{DH}	Input Data Hold Time		300	40		ns
7	ten	Output Enable Time			80	965	ns






Figure 3: Functional Difference Between IM6402 and IM6403 UART (6403 has On-Chip 4/11 Stage Divider)

INTERSIL'S SOLE AND EXCLUSIVE WARRANTY OBLIGATION WITH RESPECT TO THIS PRODUCT SHALL BE THAT STATED IN THE WARRANTY ARTICLE OF THE CONDITION OF SALE. THE WARRANTY SHALL BE EXCLUSIVE AND SHALL BE IN LIEU OF ALL OTHER WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR USE.











Figure 6: Status Flag Enable Time or Data Output Enable Time

example, a color TV crystal at 3.579545 MHz results in a baud rate of 109.2 Hz for an easy teletype interface. A 9600 baud interface may be implemented using a 2.4576 MHz crystal with the divider set to divide by 16.



INTERSIL'S SOLE AND EXCLUSIVE WARRANTY OBLIGATION WITH RESPECT TO THIS PRODUCT SHALL BE THAT STATED IN THE WARRANTY ARTICLE OF THE CONDITION OF SALE. THE WARRANTY SHALL BE EXCLUSIVE AND SHALL BE IN LIEU OF ALL OTHER WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR USE.

0050-5