

KE7245A1

Darlington Three-Phase Bridge - Visolation 2kV(RMS)

Powerex Power Semiconductors

Isolated Case (Y/N)=Yes

Circuits Per Package=1

V(BR)CEO (V)=450

V(BR)CBO (V)=600

I(C) Abs. (A) Collector Current=15

Absolute Max. Power Diss. (W)=100

R(thJC) ( $\mu\text{C/W}$ )=1.2

h(FE) Min. Static Current Gain=50

@I(C) (A) (Test Condition)=15

@VCE (test)=2.0

V(CE)sat Max. (V)=2.0

@I(C) (A) (Test Condition)=15

@I(B) (A) (Test Condition)=300m

t(r) Max. (s) Rise time=1.5 $\mu$

t(f) Max. (s) Fall time.=3.0 $\mu$

Package=Module-q